



# TRAILING EDGE Dimmers

## DMR.732, DMR.733, DMR.734, DMR.735, DMR.736

**Economic solution for controlling:**

- Dimmable LEDs 230V
- Dimmable CFLs
- Dimmable Electronic transformers

**Features**


- Supports "Aller Retour" between Push Button(s) & 1/10V or Wireless or DMX-512 or DALI (except DMR.736).
- Adjustable minimum level.
- Easily fastened to DIN (EN 60715) RAIL.
- Over temperature protection .



Designed & Manufactured  
by ELECTRON SA



Code	Power Supply	Power Output	Output Current	Dimming Resolution	Dimming Method	Output Channels	Control
<b>DMR.732</b>	230VAC / 50Hz	350VA	1.52A rms	20000 steps	Trailing Edge	1	1-10V, Push Button(s)
<b>DMR.733</b>	230VAC / 50Hz	350VA	1.52A rms	20000 steps	Trailing Edge	1	Wireless*, Push Button(s)
<b>DMR.734</b>	230VAC / 50Hz	350VA	1.52A rms	20000 steps	Trailing Edge	1	DMX-512, Push Button(s)
<b>DMR.735</b>	230VAC / 50Hz	350VA	1.52A rms	20000 steps	Trailing Edge	1	DALI, Push Button(s)
<b>DMR.736</b>	230VAC / 50Hz	350VA	1.52A rms	20000 steps	Trailing Edge	1	Wireless*

**Range****CASAMBI**

Casambi uses mesh network technology so each Casambi product acts also as a repeater. Longer ranges can be achieved by using multiple Casambi units.

\* Range is highly depended on the surrounding and obstacles, such as walls and building materials.

\*\*150m range can only be achieved between Casambi devices in evolution networks operating in long range mode in open air.

**Compatible devices:**

iPhone iOS 10.0 or later, iPad iPadOS 10.0 or later, Mac macOS 11.0 or later  
Android 4.4 KitKat or later devices with full BT 4.0 support

app available on:

