





Bluetooth

- Controlled with Casambi app which can be downloaded free of charge from Apple App Store and Google Play Store
- Direct access to all the important Casambi lighting control functionalities.
- Flexibility to interior design & communication between casambi's devices.
- Different Casambi profiles such as single channel, TW, RGBW e.t.c.
- 6 DMX devices maximum per Bluetooth controller.
- Control up to 8 DMX channels.
- Small size.



Code	Supply Voltage	Output.	Control	Dimensions	IP Rate
DEM.295	12-36VDC	DMX Up to 8 channels.	Casambi app. Bluetooth 4.0 protocol	64x29x14mm	IP20



- ➔ Different Casambi enabled products can be used from a simple one luminaire direct control to a complete and full featured light control system where up to 250 units form automatically an intelligent mesh network.
- ➔ Casambi products, should not be placed in a metal enclosure or next to large metal structures. Metal will effectively block all radio signals which are crucial to the operation of the product.

CASAMBI

Range



Casambi uses mesh network technology so each Casambi product acts also as a repeater. Longer ranges can be achieved by using multiple Casambi units.

* Range is highly depended on the surrounding and obstacles, such as walls and building materials.

**150m range can only be achieved between Casambi devices in evolution networks operating in long range mode in open air.



Compatible devices:

iPhone iOS 10.0 or later, iPad iPadOS 10.0 or later, Mac macOS 11.0 or later
Android 4.4 KitKat or later devices with full BT 4.0 support

app available on:

