

- HEKTOR is a trimless adjustable plaster luminaire.
- 3 SDCM
- L90/B10 50.000h



LIGHTSOURCE BY  
**bridgelux.**

Model	Power	CCT*	LED Source			Type	CRI	Beam Angle	Colour	Dimming Option	Accessories								
			CR180	CR190	CR197														
<b>HEKTOR</b> <i>(HEKTOR)</i>	<b>17.5W</b> <i>(18)</i>	2700K <i>(27B)</i>	2482lm	2048lm	1815lm	Adjustable <i>(AD)</i>	80 <i>(80)</i>	34° <i>(34)</i>	White <i>(WH)</i>	Without Driver <i>(00)</i>	<b>COVER</b> Standard <i>(0/)</i> ↓ <i>(XX)</i> ↑ <b>EXTRAS</b> No Extras <i>(/0)</i> Emergency <i>(/1)</i>								
		3000K <i>(30B)</i>	2637lm	2140lm	1939lm		90 <i>(90)</i>			Non Dimmable <i>(ND)</i>									
		4000K <i>(40B)</i>	2714lm	2265lm	-		97 <i>(97)</i>			Analogue (1-10V) <i>(A1)</i>									
		5700K <i>(57B)</i>	2637lm	-	-					DMX <i>(DX)</i>									
	<b>25.3W</b> <i>(25)</i>	2700K <i>(27B)</i>	3384lm	2792lm	2475lm		Adjustable <i>(AD)</i>	80 <i>(80)</i>		34° <i>(34)</i>		White <i>(WH)</i>	DALI <i>(DL)</i>						
		3000K <i>(30B)</i>	3595lm	2919lm	2644lm								Push Button <i>(PB)</i>						
		4000K <i>(40B)</i>	3701lm	3088lm	-								Phase Cut <i>(PC)</i>						
		5700K <i>(57B)</i>	3595lm	-	-								Wireless*** <i>(WL)</i>						

\* Models with CCTs of 3500K, 5000K & 6500K are available upon request.  
\*\* The wireless dimming option includes driver and Bluetooth dimming accessory.

Ordering Code Example: HEKTOR 25-30B-AD-90-34-WH-ND-00

