

KEPLER

Installation Manual

Rechargeable 

- KEPLER is a portable rechargeable lamp ideal for outdoor or indoor use.
- Material: Aluminium / black, white or brown colour.
- Charger and USB charging cable included 5V DC/1A (110/240V 50/60Hz).
- Battery: 2x2200mAh Li-ion, 3.7V
- Battery charging time: 5 hours (5V/1A).
- Touch switch, Stepless dimmable, Memory of brightness & Colour Temperature.
- Battery life according to light output: 10-120hrs.
- Ingress Protection: IP54

IP54

Code	Colour	Watt	CCT - Lumen	CRI	Battery	Voltage	Dimensions	IP Rate
TAB.008	Black	2W	2200-2700-3000K - 170lm	>80	2x2200mAh 3,7V	5VDC	Φ135mm x (H)260mm	IP54
TAB.009	White							
TAB.010	Brown							

Instructions

1. Output current of the adapter must be less than the cable load capacity.
2. Please charge the lamp completely before the first use.
3. It is advisable to use the original adapter. Otherwise, it may damage the product. The charger must be 5V DC/1A (110/240V 50/60Hz)
4. The best ambient temperature range is 10–45oC. Lower or higher temperature will shorten the battery lifetime. **Do not use this lamp under direct sunlight.**
5. The lamp should be charged in regular intervals to prolong the battery lifetime.
If the lamp is not used for a long time, please charge every three months to avoid the battery damage.
In order to guarantee the battery quality, if the lamp has run out of the battery, please charge for 10 minutes before turn on.
6. To correctly charge the lamp, we recommend that you:
 - 6.1. Put the plug into the electrical socket.
 - 6.2. When fully charged, disconnect the plug from the electrical socket and remove the cable.
7. The light source of this luminaire is not replaceable. When the light source reaches its end of life, the whole luminaire shall be replaced.
8. We recommend a soft cloth to clean the lamp. The cloth can be humid with a little water if needed. Please do not use alcohol or other aggressive cleaning materials.

Power ON-OFF



Press the touch switch to turn on
Press again to turn off

Stepless Dimming



Press the touch switch to turn on




When the lamp is switched on, long press the switch until obtain the desired brightness and then release the switch.
Memory function:
The light intensity will correspond to the previously set intensity after restart except if the lamp runs out of battery.

CCT changing





Press the touch switch to turn on

Double click the switch. When the indicator light is blue, you can press the switch to choose the desired color temperature, 3000K, 2700K and 2200K in sequence and then continue the cycling in this order.
Double click the switch again. The indicator will be off and the lamp will exit from the mode of CCT changing. If there is no operation in 1 minute under the mode of CCT changing, the lamp will exit automatically.
Memory function: The light intensity will correspond to the previously set intensity and color temperature after restart except if the lamp runs out of battery.



Battery charging

Please charge the lamp according to the different types of the accessories.
When it is fully charged, the indicator light turns green.

1.  5V 1A
2.  Charger included
100–240V–50/60Hz

CAUTION!

Make sure the charger used is 5V-1A for lithium batteries, otherwise fire or explosion caused by overcharging (overcurrent, overvoltage) may occur.

