

# MANDI SYSTEM

Interior Spotlights 


- Mandi is a trimless system creating horizontal and vertical lines.
- Mandi luminaire is available in White or Black Colour.
- Mandi System accessories include: Corner, Internal & External set 90D, Corner U type , Extension Line, 90D Corner Extension.
- Installation box is not included.
- 3 circuit track adaptor.
- L90/B10 50.000h
- 3 SDCM



LIGHTSOURCE BY  
**bridgelux**

Model (LED Power)	CCT*	LED Source			Type	Beam Angle		Colour	Dimming Option	Accessories
		CR180	CR190	CR197						
<b>MANDI 12.2W</b> <i>(MANDI 12)</i>	2700K (27B)	1575lm	1313lm	-	Adjustable <i>(AD)</i>	80 (80)	20° (20)	White (WH) Black (BL)	Without Driver (00)	Standard Diffuser (0X) Honeycomb (2X) ↓ (XX) ↑ EXTRAS No Extras (10) Emergency Kit (X1)
	3000K (30B)	1657lm	1362lm	-		90 (90)	30° (30)		Non-Dimmable (ND)	
	4000K (40B)	1706lm	1460lm	-		97 (97)			Analogue (1-10V) (A1)	
	5700K (57B)	1788lm	-	-					DMX (DX) DALI (DL) Push Button (PB) Phase Cut (PC) Wireless ** (WL)	
<b>MANDI 12.5W</b> <i>(MANDI 12)</i>	2700K (27B)	-	-	1121lm						
	3000K (30B)	-	-	1196lm						
<b>MANDI 17.1W</b> <i>(MANDI 17)</i>	2700K (27B)	2382lm	1985lm	-						
	3000K (30B)	2481lm	2060lm	-						
	4000K (40B)	2581lm	2209lm	-						
	5700K (57B)	2705lm	-	-						
<b>MANDI 17.5W</b> <i>(MANDI 17)</i>	2700K (27B)	-	-	1660lm						
	3000K (30B)	-	-	1783lm						

\* Available in 3500K, 5000K and 6500K upon request  
\*\* The wireless dimming option includes driver and Bluetooth dimming accessory.



Ordering Code Example: MANDI 17-30B-AD-80-30-BL-ND-00

