

# 1ch DALI WARM DIMMING

## LED Drivers Constant Current

Constant Current LED Drivers 

### (Amplitude dimming)



- Overload, Short-circuit protection.
- Overheating protection.
- Supports push dim operation.

Code	Supply Voltage	Output Current	Output Voltage	Power Output	Dimming
PCK.353	220-240VAC 50/60Hz	350-700mA*	9-40VDC*	14-20W*	DALI, PUSH

\*Please refer to the matrix below.

P out W	V out DC	I out DC
14	9-40	350 mA
20	9-40	500 mA
20	9-36	550 mA
20	9-28	700 mA

