

# 1ch DALI WARM DIMMING

## LED Drivers Constant Current

Constant Current LED Drivers 

### (Amplitude dimming)



- Overload & Short circuit protection.
- Overheating protection.
- Supports push dim operation.

Code	Supply Voltage	Output Current	Output Voltage	Power Output	IP Rate	Dimming
PCK.471	220-240VAC 50/60Hz	120-300mA*	9-45VDC*	5-10W*	IP20	DALI, PUSH

\*Please refer to the matrix below.

P out W	V out DC	I out DC
5.4	9-45	120 mA const.
9	9-45	200 mA const.
10	9-40	250 mA const.
10	9-33	300 mA const.

