

# 2ch DALI to CONSTANT CURRENT LED Driver Converter



- DALI DT6.
- Push switch dimming.
- Constant Current output selection from 250mA up to 1500mA.
- Built in PFC function.
- Overload, Short-circuit protection.
- Overheating protection.

Code	Supply Voltage	Output Current	Output Voltage	Power Output	Typical ripple at max output current	IP Rate
PCK.388	220-240VAC 50/60Hz	250-1500mA*	8-48VDC*	12-50W*	≤ 3%**	IP20

\*Please refer to the matrix below.  
 \*\*Referred to  $V_n = 230\text{ V}$ , 100% load

P out W/CH Max*	V out DC	I out DC	ta °C	tc °C	η max. Efficiency**
12	8-48	250 mA cost.	-25...+45	85	0.87
14	8-48	300 mA cost.			
17	8-48	350 mA cost.			
19	8-48	400 mA cost.			
22	8-48	450 mA cost.			
24	8-48	500 mA cost.			
29	8-48	600 mA cost.			
34	8-48	700 mA cost.			
38	8-48	800 mA cost.			
43	8-48	900 mA cost.			
48	8-48	1000 mA cost.			
51	8-46	1100 mA cost.			
49	8-41	1200 mA cost.			
49	8-38	1300 mA cost.			
49	8-35	1400 mA cost.			
50	8-33	1500 mA cost.			

\* CH1 + CH2 ≤ 50W.  
 \*\*Referred to  $V_n = 230\text{ V}$ , 100% load.

