

4ch DALI to CONSTANT CURRENT LED Driver Converter



- DALI DT6.
- Push switch dimming.
- Constant Current output selection from 250mA up to 1500mA.
- Built in PFC function.
- Overload, Short-circuit protection.
- Overheating protection.

Code	Supply Voltage	Output Current	Output Voltage	Power Output	Typical ripple at max output current	IP Rate
PCK.387	220-240VAC 50/60Hz	250-1500mA*	8-43VDC*	11-64W*	≤ 3%**	IP20

*Please refer to the matrix below.
 **Referred to $V_{in} = 230\text{ V}$, 100% load

P out W/CH Max*	V out DC	I out DC	ta °C	tc °C	η max. Efficiency**
11	8-43	250 mA cost.	-25...+45	85	0.87
13	8-43	300 mA cost.			
15	8-43	350 mA cost.			
17	8-43	400 mA cost.			
19	8-43	450 mA cost.			
22	8-43	500 mA cost.			
26	8-43	600 mA cost.			
30	8-43	700 mA cost.			
34	8-43	800 mA cost.			
39	8-43	900 mA cost.			
43	8-43	1000 mA cost.			
47	8-43	1100 mA cost.			
52	8-43	1200 mA cost.			
56	8-43	1300 mA cost.			
60	8-43	1400 mA cost.			
64	8-43	1500 mA cost.			

* CH1 + CH2 + CH3 + CH4 ≤ 64W.
 **Referred to $V_{in} = 230\text{ V}$, 100% load.

