

5ch DMX/RDM

Controller Constant Voltage

Constant Voltage LED Drivers 

- DMX512/RDM constant voltage LED controller. Communication between DMX control desk and controller (RDM).
- Multiple DMX input/output ports, with RJ45, XLR 5pin and screw terminal.
- Five PWM output channels, common anode.
- PWM output resolution 8bit-16bit selectable.
- Output PWM frequency from 500Hz up to 30KHz selectable.
- Output dimming curve gamma value from 0,1~9,9 selectable.
- Decoding mode selectable soft patch.
- Digital display to show data. Easy to set and display the DMX address.

FLICKER FREE SUITABLE FOR TV STUDIOS



Code*	Description	Supply Voltage	Output Voltage	Nr. of Channels	Channel Power	Output Currents
DEM.185 /CA	DMX/RDM LED controller with 5 outputs 0...12V or 0...24V	12VDC or 24VDC	Depending on the supply voltage 0...12V or 0...24V	5 channels. Can be used as 3 or 4 channel driver	96W at 12V 192W at 24V	5 channels x 8A each channel

*Note: CA=Common Anode

