Bluetooth to 0-10V, 1-10V or DALI Control Unit

Bluetooth

- Controlled with Casambi app, as well as with traditional wall switches.
 The Casambi app can be downloaded from Apple App Store and Google Play Store.
- 0-10V (and 1-10V) or digital Standalone DALI control interface.
- Standalone DALI makes it possible to implement multi-channel lighting systems with adjustable color (RGB and RGBW)
 or color temperature (CCT), while keeping the wiring and number of components at their minimum.

Code	Supply Voltage	Output Voltage*	Signal Output**	Control	Dimensions	IP Rate
DEM.192	220-240VAC 50Hz 0,6A Max. mains current	220-240VAC 50Hz	0-10VDC or DALI 9-12VDC	Casambi app. Bluetooth 4.0 protocol	56.5x35.8x22.3mm	IP20
DEM.222	220-240VAC 50Hz 0,6A Max. mains current	220-240VAC 50Hz	0-10VDC or DALI 9-12VDC	Casambi app. Bluetooth 4.0 protocol	56.5x35.8x22.3mm	IP20

*For External Relay use only

** Max. number of drivers connented: 1pc







- Different Casambi enabled products can be used from a simple one luminaire direct control to a complete and full featured light control system where up to 127 units form automatically an intelligent mesh network.
- Casambi products, should not be placed in a metal enclosure or next to large metal structures. Metal will effectively block all radio signals which are crucial to the operation of the product.

Range





Casambi uses mesh network technology so each Casambi product acts also as a repeater. Longer ranges can be achieved by using multiple Casambi units.

* Range is highly depended on the surrounding and obstacles, such as walls and building materials.

**150m range can only be achieved between Casambi devices in evolution networks operating in long range mode in open air.

ompatible devices:

iPhone iOS 10.0 or later, iPad iPadOS 10.0 or later, Mac macOS 11.0 or later Android 4.4 KitKat or later devices with full BT 4.0 support app available on:





Dimming without app

- 1. Turn lights on from a wall switch.
- 2. Quickly flick the wall switch off (max. 1 sec.) and back on. The light level starts to increase gradually
- $\textbf{3.} \ \ \textbf{Flick the switch again at desired dim level}. \ \textbf{The selected level is saved automatically}.$
- $\textbf{4.} \ \ \text{If the second flick is not done within 8 sec. the light intensity reaches its maximum level}.$
- $\textbf{5.} \ \ \textbf{Flicking the switch can also be used to switch between predefined scenes}.$



