

# 1ch DALI to CONSTANT CURRENT or CONSTANT VOLTAGE Converters



- Dimmable: DALI-2
- Overload & Short circuit protection.
- Ripple free.

Code	Supply Voltage	Output Current	Output Voltage	Power Output	Typical ripple at max output current	IP Rate	Dimming
<b>PCK.324</b>	220-240VAC 50/60Hz	250-700mA*	3-48VDC*	12-32W*	≤ 3%**	IP20	DALI

\*Please refer to the matrix below.

\*\*Referred to  $V_n = 230\text{ V}$ , 100% load

P out W	V out DC	I out DC	V out max.	ta °C	tc °C	λ max. Power Factor	η max. Efficiency*
12	10-48	250 mA cost.	59	-25...+50	75	0.95	>0.87
14	10-48	300 mA cost.					
17	5-48	350 mA cost.					
19	5-48	400 mA cost.					
22	5-48	450 mA cost.					
24	5-48	500 mA cost.					
26	3-48	550 mA cost.					
28	3-48	600 mA cost.					
31	3-48	650 mA cost.					
32	3-46	700 mA cost.					
<b>10W at 12VDC</b>		Constant Voltage					
<b>20W at 24VDC</b>		Constant Voltage					

\*Referred to  $V_n = 230\text{ V}$ , 100%

