

1ch DALI to CONSTANT CURRENT Converters



- Overload, Short-circuit protection
- Overheating protection

| Code | Supply Voltage | Output Current | Output Voltage | Max. Power Consumption | Control |
|----------------|--------------------|----------------|----------------|------------------------|------------|
| PCK.296 | 220-240VAC 50/60Hz | 200-1200mA* | 10-54VDC* | 36W | DALI, PUSH |

*Please refer to the matrix below.

| Output Power | Output Voltage | Output Current |
|--------------------|----------------|----------------|
| 2-10.8W | 10-54V | 200mA |
| 3.5-18.9W | 10-54V | 350mA |
| 5-27W | 10-54V | 500mA |
| 6-32.4W | 10-54V | 600mA |
| 7-36.4W | 10-52V | 700mA |
| 9-36W | 10-40V | 900mA |
| 10.5-36.75W | 10-35V | 1050mA |
| 12-36W | 10-30V | 1200mA |

