

1ch DALI WARM DIMMING NFC PROGRAMMABLE LED Drivers Constant Current

Constant Current LED Drivers 

(Amplitude dimming)



- NFC Programmable.
- DALI-2
- Overload & Short circuit protection.
- Current selectable output with 1mA step.
- Supports push dim operation.
- Strain relief set to be ordered separately (467.ACC.200).

Code	Supply Voltage	Output Current	Output Voltage	Power Output	Typical ripple of max output current	IP Rate	Dimming
PCK.973	220-240VAC 50/60Hz	300-700mA*	7-42VDC*	12-28W*	≤ 2%**	IP20	DALI

*Please refer to the matrix below.

**Referred to $V_{in} = 230\text{ V}$, 100% load

P out W	V out DC	I out DC	V out max.	ta °C	tc °C	λ max. Power Factor	η max. Efficiency*
12.6	7.5-42	300 mA cost.	60	-25...+50	80	0.97	86
16.8	7.5-42	400 mA cost.					
21	7.5-42	500 mA cost.					
25.2	7.5-42	600 mA cost.					
28	7.5-40	700 mA cost.					

*Referred to $V_{in} = 230\text{ V}$, 100%

