

1ch DMX/RDM to CONSTANT CURRENT LED Drivers-Converters

Constant Current LED Drivers 

- PWM control.
- 16bit dimming resolution.
- Logarithmic dimming curve.
- Overheating protection.
- Overload protection.
- Suitable for TV studios.




 Designed & Manufactured
 by ELECTRON SA

Code	Supply Voltage	Output Current	Output Voltage	Output Power	Dimming
DEM.056	220-240VAC 50/60Hz	700-1400mA*	10-42VDC*	7W-45W	DMX-512/RDM

*Please refer to the matrix below.

P out W	V out DC	I out DC
29.4W	10-42V	700mA
31.5W	10-42V	750mA
33.6W	10-42V	800mA
35.7W	10-42V	850mA
37.8W	10-42V	900mA
44.1W	10-42V	1050mA
45.0W	10-37.5V	1200mA
45.1W	10-32.2V	1400mA

