

2ch TW DT8 DALI to CONSTANT CURRENT NFC PROGRAMMABLE

LED Drivers Constant Current

(Amplitude dimming)



- NFC Programmable.
- DALI-2.
- Overload, Short circuit & Overtemperature protection.
- Current selectable output with 0.1mA step.
- Common anode configuration.

Code	Supply Voltage	Output Current	Output Voltage	Power Output	Typical ripple at max output current	IP Rate	Dimming
PCK.546	220-240VAC 50/60Hz	350-1050mA*	6-54VDC*	19-36W*	≤ 3%**	IP20	DALI-2

*Please refer to the matrix below.

**Referred to $V_{in} = 230\text{ V}$, 100% load

P out W	V out DC	I out DC	V out max.	ta °C	tc °C	λ max. Power Factor	η max. Efficiency*
18.9	6-54	350 mA cost.	60	-25...+45	85	0.95	86
27	6-54	500 mA cost.					
36.4	6-52	700 mA cost.					
36	6-40	900 mA cost.					
36.8	6-35	1050 mA cost.					

*Referred to $V_{in} = 230\text{ V}$, 100%

