

# 1ch 1-10V DIMMABLE

## LED Drivers Constant Current

Constant Current LED Drivers 



Code	Supply Voltage	Output Current	Output Voltage	Power Output	Typical ripple at max output current	IP Rate	Dimming
<b>PCK.322</b>	220-240VAC 50/60Hz	350-700mA*	30-120VDC*	42-80W*	≤ 3%**	IP20	1-10V, PUSH

\*Please refer to the matrix below.

\*\*Referred to  $V_{in} = 230\text{ V}$ , 100% load

P out W	V out DC	I out DC	V out max.	ta °C	tc °C	λ max. Power Factor	η max. Efficiency*
42	30-120	350 mA cost.	180	-25...+50	85	0.95	>92
45	30-120	375 mA cost.					
48	30-120	400 mA cost.					
51	30-120	425 mA cost.					
54	30-120	450 mA cost.					
57	30-120	475 mA cost.					
60	30-120	500 mA cost.					
63	30-120	525 mA cost.					
66	30-120	550 mA cost.					
69	30-120	575 mA cost.					
72	30-120	600 mA cost.					
75	30-120	625 mA cost.					
78	30-120	650 mA cost.					
80	30-118	675 mA cost.					
80	30-114	700 mA cost.					

\*Referred to  $V_{in} = 230\text{ V}$ , 100%

