

# 1ch 1-10V WARM DIMMING

## LED Drivers Constant Current

(Amplitude dimming)



Code	Supply Voltage	Output Current	Output Voltage	Power Output	Dimming
PCK.468	220-240VAC 50/60Hz	120-350mA*	9-42VDC*	5-10W*	1-10V

\*Please refer to the matrix below.

P out W	V out DC	I out DC
5	9-42	120 mA cost.
6.3	9-42	150 mA cost.
7.6	9-42	180 mA cost.
8.4	9-42	200 mA cost.
9.8	9-41	240 mA cost.
10	9-37	270 mA cost.
10	9-33	300 mA cost.
10	9-28	350 mA cost.

