

1ch DALI DIMMABLE IP68 NFC PROGRAMMABLE LED Drivers Constant Current

- NFC Programmable.
- Current selectable output with 1mA step.
- Supports push dim operation.
- IP68
- DALI-2
- Overload & Short circuit protection.
- Overheating protection.



Code	Supply Voltage	Output Current	Power Output	Typical ripple at max output current	ta °C	IP Rate	Dimming
PCK.543	220-240VAC 50/60Hz	150-1050mA*	8-38VDC*	≤ 3%**	-25..+50	IP68	DALI, PUSH

*Please refer to the matrix below.

**Referred to V_n = 230 V, 100% load

P out W	V out DC	I out DC	V out max.	t _c °C	η max. Efficiency*
8	10-54	150 mA const.			
14	10-54	250 mA const.			
19	10-54	350 mA const.			
27	10-54	500 mA const.			
38	10-54	700 mA const.			
38	10-42	900 mA const.			
38	10-36	1050 mA const.			

*Referred to V_n = 230 V, 100%

