

1ch DALI WARM DIMMING

LED Drivers Constant Current

Constant Current LED Drivers 

(Amplitude dimming)



- Overload, Short-circuit protection.
- Overheating protection.
- Supports push dim operation.

| Code | Supply Voltage | Output Current | Output Voltage | Power Output | Dimming |
|---------|--------------------|----------------|----------------|--------------|------------|
| PCK.353 | 220-240VAC 50/60Hz | 350-700mA* | 9-40VDC* | 14-20W* | DALI, PUSH |

*Please refer to the matrix below.

| P out W | V out DC | I out DC |
|------------|-------------|-------------|
| 14 | 9-40 | 350 mA |
| 20 | 9-40 | 500 mA |
| 20 | 9-36 | 550 mA |
| 20 | 9-28 | 700 mA |

