

1ch DALI WARM DIMMING LED Drivers Constant Current

(Amplitude dimming)



- Overload & Short circuit protection.
- DALI-2
- Supports push dim operation.
- Selectable output current in 50mA steps.
- Adjustable current output resistor (to be ordered separately).
- Strain relief set to be ordered separately (467.ACC.200).

Code	Supply Voltage	Output Current	Output Voltage	Power Output	Typical ripple at max output current	IP Rate	Dimming
PCK.367	220-240VAC 50/60Hz	500-1050mA*	25-50VDC*	25-45W*	≤ 3%**	IP20	DALI

*Please refer to the matrix below.

**Referred to $V_{in} = 230\text{ V}$, 100% load

P out W	V out DC	I out DC	V out max.	t _a °C	t _c °C	λ max. Power Factor	η max. Efficiency*
25	25-50	500 mA cost.	60	-25...+50	80	0,98	0,91
35	25-50	700 mA cost.			85		
45	25-50	900 mA cost.			85		
45	25-43	1050 mA cost.			85		

*Referred to $V_{in} = 230\text{ V}$, 100%

