

# 1ch DALI WARM DIMMING

## LED Drivers Constant Current

### (Amplitude dimming)



- Overload & Short circuit protection.
- Overheating protection.
- Supports push dim operation.

Code	Supply Voltage	Output Current	Output Voltage	Power Output	IP Rate	Dimming
<b>PCK.445</b>	220-240VAC 50/60Hz	350-700mA*	2-24VDC*	8-10W*	IP20	DALI, PUSH

\*Please refer to the matrix below.

P out W	V out DC	I out DC
8.4	2-24	350 mA const.
9.6	2-24	400 mA const.
9.9	2-22	450 mA const.
10	2-20	500 mA const.
9.9	2-18	550 mA const.
9.6	2-16	600 mA const.
9.8	2-15	650 mA const.
9.8	2-14	700 mA const.

