

# 1ch DALI WARM DIMMING NFC PROGRAMMABLE LED Drivers Constant Current

## (Amplitude dimming)



- NFC Programmable.
- DALI-2
- Overload & Short circuit protection.
- Current selectable output with 1mA step.
- Supports push dim operation.

Code	Supply Voltage	Output Current	Output Voltage	Power Output	Typical ripple at max output current	IP Rate	Dimming
PCK.956	220-240VAC 50/60Hz	450-1050mA*	27-54VDC*	24-45W*	≤ 5%**	IP20	DALI

\*Please refer to the matrix below.

\*\*Referred to  $V_{in} = 230\text{ V}$ , 100% load

P out W	V out DC	I out DC	V out max.	ta °C	tc °C	λ max. Power Factor	η max. Efficiency*
24.3	27-54	450 mA cost.	60	-25...+50	65	0.95	88
27	27-54	500 mA cost.					
32.4	27-54	600 mA cost.					
37.8	27-54	700 mA cost.					
43.2	27-54	800 mA cost.					
45	27-50	900 mA cost.					
45	27-43	1050 mA cost.					

\*Referred to  $V_{in} = 230\text{ V}$ , 100%

