

1ch DALI / 1-10V / PUSH WARM DIMMING LED Drivers Constant Current

(Amplitude dimming)



- Overload & Short circuit protection.
- DALI-2

Code	Supply Voltage	Output Current	Output Voltage	Power Output	Typical ripple at max output current	IP Rate	Dimming
PCK.356	220-240VAC 50/60Hz	350-1050mA*	2-74VDC*	25-60W*	≤ 3%**	IP20	DALI, 1-10V, PUSH

*Please refer to the matrix below.

**Referred to $V_{in} = 230\text{ V}$, 100% load

P out W	V out DC	I out DC	V out max.	ta °C	tc °C	λ max. Power Factor	η max. Efficiency*
25	2-74	350 mA cost.	90	-25...+50	90	0.95	>92
35	2-72	500 mA cost.					
39	2-72	550 mA cost.					
46	2-72	650 mA cost.					
50	2-72	700 mA cost.					
54	2-72	750 mA cost.					
60	2-70	850 mA cost.					
60	2-66	900 mA cost.					
60	2-60	1.00 A cost.					
60	2-57	1.05 A cost.					

*Referred to $V_{in} = 230\text{ V}$, 100% load

