

1ch DMX to CONSTANT CURRENT

LED Drivers-Converters

Constant Current LED Drivers 




Designed & Manufactured
by ELECTRON SA

- PWM control.
- 16bit dimming resolution.
- Logarithmic dimming curve.
- Overheating protection.
- Suitable for TV studios.

Code	Supply Voltage	Output Current	Output Voltage	Output Power	Dimming
350mA					
DEM.053	220-240VAC 50/60Hz	350mA	5-42VDC	2W-15W	DMX-512
500mA					
DEM.052	220-240VAC 50/60Hz	500mA	25-39VDC	12W-20W	DMX-512
700mA					
DEM.051	220-240VAC 50/60Hz	700mA	25-39VDC	17W-27W	DMX-512
900mA					
DEM.050	220-240VAC 50/60Hz	900mA	25-39VDC	23W-35W	DMX-512

