


# 1ch DMX to CONSTANT CURRENT LED Drivers-Converters




Code	Supply Voltage	Output Channels	Constant Current	Output Power	Output Voltage	Control
<b>PCK.337</b>	220-240VAC 50/60Hz	1	150mA -	1.5-8.1W -	10-54VDC	DMX 512 / RDM and PUSH
			250mA -	2.5-13.5W -	10-54VDC	
			300mA -	3-16.2W -	10-54VDC	
			350mA -	3.5-18.9W -	10-54VDC	
			500mA -	5-25W -	10-50VDC	
			600mA -	6-25.2W -	10-42VDC	
			700mA -	7-25.2W -	10-36VDC	
900mA -	9-25.2W -	10-28VDC				
<b>PCK.338</b>	220-240VAC 50/60Hz	1	100mA -	1-5.4W -	10-54VDC	DMX 512 / RDM and PUSH
			180mA -	1.8-9.72W -	10-54VDC	
			300mA -	3-15W -	10-50VDC	
			350mA -	3.5-15.05W -	10-43VDC	
			450mA -	4.5-15.3W -	10-34VDC	
			500mA -	5-15W -	10-30VDC	
			600mA -	6-15W -	10-25VDC	
700mA -	7-15.4W -	10-22VDC				
<b>PCK.552</b>	220-240VAC 50/60Hz	1	100mA -	1-4.2W -	10-42VDC	DMX 512 / RDM
			150mA -	1.5-6.3W -	10-42VDC	
			200mA -	2-8.4W -	10-42VDC	
			250mA -	2.5-10.5W -	10-42VDC	
			300mA -	3-12W -	10-40VDC	
			350mA -	3.5-12W -	10-34VDC	
			400mA -	4-12W -	10-30VDC	



PCK.337



PCK.338



PCK.552

