

1ch DMX/RDM to CONSTANT CURRENT LED Drivers-Converters

Constant Current LED Drivers 



- PWM control.
- 16bit dimming resolution.
- Logarithmic dimming curve.
- Overheating protection.
- Overload protection.
- Suitable for TV studios.

| Code | Supply Voltage | Output Current | Output Voltage | Output Power | Dimming |
|---------|--------------------|----------------|----------------|--------------|-------------|
| DEM.056 | 220-240VAC 50/60Hz | 700-1400mA* | 10-42VDC* | 7W-45W | DMX-512/RDM |


Designed & Manufactured
by ELECTRON SA

*Please refer to the matrix below.

| P out W | V out DC | I out DC |
|------------|-------------|-------------|
| 29.4W | 10-42V | 700mA |
| 31.5W | 10-42V | 750mA |
| 33.6W | 10-42V | 800mA |
| 35.7W | 10-42V | 850mA |
| 37.8W | 10-42V | 900mA |
| 44.1W | 10-42V | 1050mA |
| 45.0W | 10-37.5V | 1200mA |
| 45.1W | 10-32.2V | 1400mA |

