


1ch LED Boosters

Constant Current

Constant Current LED Drivers 



Designed & Manufactured
by ELECTRON SA

- LED Boosters of PWM signal of the LED controller.
- For constant current LEDs.
- For 350mA, 500mA, 700mA.
- One Channel LED driving Booster (repeater/amplifier).
- Possible to use in RGB constant current LEDs.

Code	Supply Voltage	Output Voltage	Output Current	Output Channels	Output Power	Power Consumption
DEM.036	24VDC	2,9V-21,4VDC	350mA	1	1-7,5W	8,3W
DEM.037	24VDC	5,7V-65,7VDC	350mA	1	2-23W	28,5W
DEM.038	24VDC	3,2V-22VDC	500mA	1	1,6-11W	12,10W
DEM.039	24VDC	10V-66VDC	500mA	1	5-33W	41,5W
DEM.040	24VDC	4,3V-21,4VDC	700mA	1	3-15W	16,50W
DEM.041	24VDC	10V-60VDC	700mA	1	7-42W	52,5W

