



- Smart isolated PIR Sensor Switch Controller, with detachable PIR sensor detector (1,5m cable).
- The controller will turn on the switch output when it detects motion. And turn off automatically after the adjustable delay.
- Wide range operation input voltage from 100VAC to 240VAC.
- Stand by consumption <0,5W
- Detection range: 0,5-2,5m
- Detection angle: 80°
- Delay time: 10-30sec
- PIR Sensor available in white colour as standard. Black colour available upon request.
- Operating temperature range: -20° to +50°C
- Indoor use



| Code | Model | Input Voltage | Delay Time | Detection Angle |
|---------|---------------------|----------------------|------------|-----------------|
| SNR.006 | PIR Motion Detector | AC100V~240V, 50/60Hz | 10sec~3min | 80° |

Max. Lighting load:

Types of load

| Range voltage | Incandescent lamp/ HV-halogen lamp | Electronic ballast | Inductance ballast | Electronic transformer | LED driver |
|------------------|---------------------------------------|-----------------------|-----------------------|---------------------------|------------|
| AC 100V, 50/60Hz | 250VA | 80VA | 60VA | 250VA | 80VA |
| AC 240V, 50/60Hz | 250VA | 150VA | 100VA | 250VA | 150VA |

